

Psooo M2 Wireless Solar Power Bank - 36800mAh



Specifications:

- Battery capacity: 36800mAh
- Input: MicroUSB, USB-C, Lightning
- Output: USB-C, Lightning, 4x USB-A, MicroUSB
- Input voltage: MicroUSB/Lightning: 5V/2A, Type-C: 5V/3A
- Output voltage: 5V/3A (USB+Type-C)
- Wireless charging power: 5W
- Dimensions: 166 x 82 x 52mm

Product overview



1. USB output 1
2. USB output 2
3. USB output 3
4. MicroUSB input
5. Lightning input
6. USB-C input/output
7. USB input cable
8. MicroUSB output cable
9. USB-C output cable
10. Lightning output cable
11. Wireless charging
12. LED flashlights
13. Solar panel
14. Power button
15. Battery indicators

LED flashlight instructions:

1. Double press the power button to turn on the LED flashlight bright mode
2. Press the power button again to turn on the LED flashlight normal mode
3. To enter the SOS light mode, turn on the flashlight, press the power button once and then once again
4. To turn off the LED flashlight double press the power button

Wireless charging instructions:

1. Press the power button to turn on the wireless charging
2. Place your smartphone in the wireless charging area to start charging



Solar charging:

To recharge the power bank via the solar panel, please put the power bank in direct sunlight and ensure the solar panel is positioned towards the sun. The solar charging indicators will blink while the charging is in process and turn off when the power bank is fully charged. Note: the solar panel should be used only for emergency charging, and it should not be the primary source of charging.

Charging instructions:

Use your cables to recharge your devices via USB and USB-C ports, or use built-in cables to recharge your devices. To recharge the power bank, use the built-in USB cable or your USB-C/microUSB/Lightning cable, and connect the power bank to your own AC adapter or computer's USB port.